
DELTALIGHT




# SPM20 - SPY 392 AIR SOFT 93040

**REFERENCE** 29816 9030 B

AVAILABLE IN
**BLACK** 29816 9030 B
**FLEMISH BRONZE** 29816 9030 FBR
**FLEMISH GOLD** 29816 9030 FG
**GOLD COLOURED** 29816 9030 GC
**WHITE** 29816 9030 W




View on website

| General info | |
|---|---|
| **LOCATION** | indoor |
| **INSTALLATION** | Ceiling Recessed |
| **CUTOUT SHAPE/SIZE (MM)** | rectangle - KIT |
| **INGRESS PROTECTION** | IP20 |
| **WEIGHT (KG)** | 0.5 |
| **ADJUSTABILITY** | 0° to 85° swiveling, 355° rotatable |
| **INFORMATION** | REFLECTOR WFL-40°<br>EXCL.DIMMABLE LED POWER SUPPLY 350mA-DC |

| Electrical info | |
|---|---|
| **CLASS** | III |
| **DIM TYPE** | depending on power supply |
| **ENERGY CLASS** | F |

| Lightsource info | |
|---|---|
| **LIGHTSOURCE NAME** | LED |
| **LIGHTSOURCE** | 2 x (LED array 6W / CRI>90 (R9: 50) / 3000K-1800K / 623lm) |
| **TM-30 VALUES** | Rf: 90 / Rg: 99 |
| **SDCM** | SDCM2 |
| **RISKGROUP** | RG1 |
| **LM80** | L90B10 > 50000 |
| **BEAMANGLE** | 40° |
| **LED TECHNICS (LIGHT SOURCE)** | 1246lm // 12W // 105lm/W |
| **LED TECHNICS (LUMINAIRE)** | 1010lm // 13,8W // 73lm/W |

**Requirements**

SPM20 - AIR KIT 1
SPY 39 TUBE
LED POWER SUPPLY 350mA-DC DIM

For detailed installation instructions, please consult the manual : **29816_XXX0_HAND.pdf**


DELTALIGHT

# SPM20 - SPY 392 AIR SOFT 93040

29816 9030 B

## FINISH YOUR SPECIFICATION

### Emergency units




**21032 0270 B** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B ☐

**Cutout dimension (mm): 27**


**21032 0270 W** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W ☐

### LED power supplies

### # of Fixtures

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


**Min current | Max current**




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 — 1 ☐

**Dimtype: 1-10V**


**Cutout dimension (mm): 30**




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 1 ☐

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL — 1 ☐

**Dimtype: non-dimmable**


**Cutout dimension (mm): 30**




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL — 1 ☐

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 45**




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6 — 1 ☐

**Dimtype: mains (phase cut-off) or push button**

**Cutout dimension (mm): 56**





**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9 — 2(2) ☐

**Dimtype: 1-10V or DALI or push button**

**Cutout dimension (mm): 82**

# SPM20 - SPY 392 AIR SOFT 93040


29816 9030 B




**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7 1(1)


**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 72**




**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 1


**Dimtype: 1-10V or DALI or push button**




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5 1(1)

**Dimtype: DALI**


**Cutout dimension (mm): 72**




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9 3(3)

**Dimtype: 1-10V or DALI or push button**


**Cutout dimension (mm): 84**




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7 1(1)

**Dimtype: 1-10V or push button**


**Cutout dimension (mm): 55**




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5 1(1)

**Dimtype: DALI**


**Cutout dimension (mm): 55**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1 1

**Dimtype: 1-10V**


**Cutout dimension (mm): 54**




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5 1

**Dimtype: DALI**


**Cutout dimension (mm): 54**




**21012 004W** LED POWER SUPPLY MULTI-POWER WDL 2(2)

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 84**




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL 1


**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 54**

DELTALIGHT

# SPM20 - SPY 392 AIR SOFT 93040


29816 9030 B




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 — 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 50**




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 — 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 48**




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8 — 1/2

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 1

**Dimtype: DALI**

**Cutout dimension (mm): 30**

Notes: