





SPY 39 PLUG 93040

24149 9330 W

- AVAILABLE IN
- BLACK 24149 9330 B
  - BRUSHED ALU 24149 9330 BRA
  - BRUSHED ANTHRACITE 24149 9330 BRAT
  - BRUSHED COPPER 24149 9330 BRCU
  - BRUSHED GOLD 24149 9330 BRG
  - BRUSHED OLD BRONZE 24149 9330 BROB
  - FLEMISH BRONZE 24149 9330 FBR
  - FLEMISH GOLD 24149 9330 FG
  - FULL WHITE 24149 9330 FW
  - GOLD COLOURED 24149 9330 GC
  - PIANO BLACK 24149 9330 PB
  - WHITE 24149 9330 W



[View on website](#)



| General info            |                                                         |
|-------------------------|---------------------------------------------------------|
| LOCATION                | indoor                                                  |
| INSTALLATION            | Ceiling Semi-recessed                                   |
| CUTOOUT SHAPE/SIZE (MM) | round - Ø KIT                                           |
| RECESSED DEPTH (MM)     | 80                                                      |
| INGRESS PROTECTION      | IP20                                                    |
| WEIGHT (KG)             | 0.4                                                     |
| ADJUSTABILITY           | 0° to 85° swiveling, 355° rotatable                     |
| INFORMATION             | REFLECTOR WFL-40°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

| Electrical info |                           |
|-----------------|---------------------------|
| CLASS           | III                       |
| DIM TYPE        | depending on power supply |
| ENERGY CLASS    | E                         |
| CERTIFICATES    | CB, ENEC                  |

| Lightsource info            |                                                           |
|-----------------------------|-----------------------------------------------------------|
| LIGHTSOURCE NAME            | LED                                                       |
| LIGHTSOURCE                 | LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm |
| TM-30 VALUES                | rf: 90 / Rg: 99                                           |
| SDCM                        | SDCM1                                                     |
| RISKGROUP                   | RG1                                                       |
| LM80                        | L90B10 > 50000                                            |
| BEAMANGLE                   | 40°                                                       |
| LED TECHNICS (LIGHT SOURCE) | 1089lm // 8,6W // 127lm/W                                 |
| LED TECHNICS (LUMINAIRE)    | 883lm // 9,9W // 89lm/W                                   |

| Requirements                        |  |
|-------------------------------------|--|
| SPY 39 TUBE or VISOR 39             |  |
| MOUNTING KIT PLUG O.F.A.            |  |
| LED POWER SUPPLY 350 / 500mA-DC DIM |  |

# DELTALIGHT

## SPY 39 PLUG 93040

24149 9330 W

For detailed installation instructions, please consult the manual : [24149\\_XXX0\\_HAND.pdf](#)

### CEILING COMPATIBILITY

| Ceiling Type                                                                                                       | Mounting Kit                                                                                                            |          |
|--------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|----------|
|  <b>Plasterboard</b>               |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Concrete + plaster</b>         |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Lintel + plaster</b>           |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Hollow-core slab + plaster</b> |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |

### FINISH YOUR SPECIFICATION

#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the 'I' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30



**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45

# DELTALIGHT

## SPY 39 PLUG 93040








24149 9330 W

|                                                                                    |                                                                          |                |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|----------------|--------------------------|
|    | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V                                                           |                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                |                          |
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                |                          |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                |                          |
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                |                          |
|  | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 2   2          | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |                |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |                |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 4(4)   4(4)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |                |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                |                          |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9    | 2   -          | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5                       | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                |                          |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9                    | 2->6(6)   6(4) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 84                                                |                |                          |

# DELTALIGHT

## SPY 39 PLUG 93040

24149 9330 W

|                                                                                    |                                                                                                                                                   |                                      |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------|
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype:</b> 1-10V or push button<br><b>Cutout dimension (mm):</b> 55                | 3(2)   2(1) <input type="checkbox"/> |
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 55                           | 2(2)   2(1) <input type="checkbox"/> |
|    | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br><b>Dimtype:</b> non-dimmable<br><b>Cutout dimension (mm):</b> 90                          | 3->4   2->4 <input type="checkbox"/> |
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><b>Dimtype:</b> non-dimmable<br><b>Cutout dimension (mm):</b> 50                             | 2   2 <input type="checkbox"/>       |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><b>Dimtype:</b> 1-10V<br><b>Cutout dimension (mm):</b> 54                               | 3   3 <input type="checkbox"/>       |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 54                                | 3   3 <input type="checkbox"/>       |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><b>Dimtype:</b> WDL = wireless dimmable<br><b>Cutout dimension (mm):</b> 84              | 4(4)   3(3) <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><b>Dimtype:</b> WDL = wireless dimmable<br><b>Cutout dimension (mm):</b> 54      | 3   3 <input type="checkbox"/>       |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><b>Dimtype:</b> mains (phase cut-off)<br><b>Cutout dimension (mm):</b> 50 | 2->2   0 <input type="checkbox"/>    |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><b>Dimtype:</b> mains (phase cut-off)<br><b>Cutout dimension (mm):</b> 55 | 1 <input type="checkbox"/>           |

# DELTALIGHT

## SPY 39 PLUG 93040

24149 9330 W

|                                                                                    |                                                                      |       |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|-------|--------------------------|
|    | <b>21012 0288</b> LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8    | 2->3  | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 55                                                          |                                                                      |       |                          |
|    | <b>21012 0298</b> LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8    | 2   2 | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 48                                                          |                                                                      |       |                          |
|    | <b>21012 0308</b> LED POWER SUPPLY 350mA / 7,35W DIM8                | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 40                                                          |                                                                      |       |                          |
|    | <b>21012 0318</b> LED POWER SUPPLY 500mA / 10W DIM8                  | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 40                                                          |                                                                      |       |                          |
|  | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 2(2)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 2(1)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 2     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |

### Mounting kits

|                                                                                    |                                            |                          |
|------------------------------------------------------------------------------------|--------------------------------------------|--------------------------|
|  | <b>24144 0060</b> MOUNTING KIT PLUG O.F.A. | <input type="checkbox"/> |
| Cutout dimension (mm): 62 (CONCRETE: 102)                                          |                                            |                          |

# DELTALIGHT

## SPY 39 PLUG 93040

24149 9330 W

### Light altering devices



**24144 0030 B** VISOR 39 B

☐

### Finish your product



**24144 0010 B** SPY 39 TUBE B

☐

**24144 0010 FBR** SPY 39 TUBE FBR

☐

**24144 0010 FG** SPY 39 TUBE FG

☐

**24144 0010 GC** SPY 39 TUBE GC

☐

**24144 0010 W** SPY 39 TUBE W

☐

**24144 0070** SPY 39 TUBE SBL

☐

Notes: