
DELTALIGHT




# SPLITBOX 3 SPY FOCUS LP 927

**REFERENCE** 100073 9200 B

AVAILABLE IN
**BLACK** 100073 9200 B
**WHITE** 100073 9200 W



View on website

| General info | |
|---|---|
| **LOCATION** | indoor |
| **INSTALLATION** | Ceiling Recessed |
| **CUTOUT SHAPE/SIZE (MM)** | rectangle - 365 x 150 |
| **RECESSED DEPTH (MM)** | 180 |
| **THICKNESS OF MOUNTING SURFACE (MM)** | max.12 |
| **INGRESS PROTECTION** | IP20 |
| **WEIGHT (KG)** | 5.5 |
| **INFORMATION** | ADJUSTABLE<br>3 x ADJUSTABLE BEAM 8°-43°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

| Electrical info | |
|---|---|
| **CLASS** | III |
| **DIM TYPE** | depending on power supply |
| **ENERGY CLASS** | F |
| **CERTIFICATES** | CB, ENEC |

| Lightsource info | |
|---|---|
| **LIGHTSOURCE NAME** | LED |
| **LIGHTSOURCE** | 3 x (LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 702-974lm) |
| **TM-30 VALUES** | Rf: 89 / Rg: 100 |
| **SDCM** | SDCM1 |
| **RISKGROUP** | RG1 |
| **LM80** | L90B10 > 50000 |
| **BEAMANGLE** | 8°-43° |
| **LED TECHNICS (LIGHT SOURCE)** | 2922lm // 25,8W // 113lm/W |
| **LED TECHNICS (LUMINAIRE)** | 1198lm // 29,7W // 40lm/W |

**Requirements**

LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : **100073_XXX0_HAND.pdf**

DELTALIGHT

# SPLITBOX 3 SPY FOCUS LP 927


100073 9200 B

## CEILING COMPATIBILITY

| Ceiling Type | Mounting Kit |
|---|---|
|  System ceiling | - |
|  Plasterboard | - |

## FINISH YOUR SPECIFICATION


| LED power supplies | # of Fixtures |
|---|---|
| # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '\|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V. | Min current \| Max current |




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 — 2/3

**Dimtype: 1-10V**


**Cutout dimension (mm): 30**




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 2/3

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL — 2/3

**Dimtype: non-dimmable**


**Cutout dimension (mm): 30**




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL — 2/3

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 45**




**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 — 2/3

**Dimtype: 1-10V**

**Cutout dimension (mm): 30**




**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 2/3


**Dimtype: DALI**

**Cutout dimension (mm): 45**

DELTALIGHT

# SPLITBOX 3 SPY FOCUS LP 927


100073 9200 B




**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL — 2/3

**Dimtype: non-dimmable**


**Cutout dimension (mm): 30**




**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL — 2/3

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 45**




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6 — 2/3 | 2/3

**Dimtype: mains (phase cut-off) or push button**


**Cutout dimension (mm): 56**




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9 — 1(1) | 1(1)

**Dimtype: 1-10V or DALI or push button**


**Cutout dimension (mm): 82**




**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7 — 1(2/3) | 2/3(1/3)


**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 72**




**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 — 2/3 | -


**Dimtype: 1-10V or DALI or push button**




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5 — 2/3(2/3) | 2/3(1/3)

**Dimtype: DALI**


**Cutout dimension (mm): 72**




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9 — 2(2) | 3(1)

**Dimtype: 1-10V or DALI or push button**


**Cutout dimension (mm): 84**




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7 — 2/3(2/3) | 2/3(1/3)

**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 55**





**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5 — 2/3(2/3) | 2/3(1/3)

**Dimtype: DALI**

**Cutout dimension (mm): 55**

# SPLITBOX 3 SPY FOCUS LP 927


100073 9200 B




**300 90 135** LED POWER SUPPLY MULTI-POWER HV 1 | 1

**Dimtype: non-dimmable**


**Cutout dimension (mm): 90**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1 1 | 1

**Dimtype: 1-10V**


**Cutout dimension (mm): 54**




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5 1 | 1

**Dimtype: DALI**


**Cutout dimension (mm): 54**




**21012 004W** LED POWER SUPPLY MULTI-POWER WDL 1(1) | 1(1)

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 84**




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL 1 | 1

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 54**




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8 1/3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 50**




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 2/3->2/3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 50**




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 1/3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 2/3->1

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 2/3 | 2/3


**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 48**

DELTALIGHT

# SPLITBOX 3 SPY FOCUS LP 927


100073 9200 B




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8 1/3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 40**




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8 1/3

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 40**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 2/3

**Dimtype: DALI**

**Cutout dimension (mm): 30**




**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 2/3

**Dimtype: DALI**

**Cutout dimension (mm): 30**

Notes: