



## SPY 20 L TRIMLESS 93030

27217 9320 FG

AVAILABLE IN



**BLACK** 27217 9320 B

**FLEMISH BRONZE** 27217 9320 FBR

**FLEMISH GOLD** 27217 9320 FG

**GOLD COLOURED** 27217 9320 GC

**WHITE** 27217 9320 W



[View on website](#)



### General info

|                               |                                                                                   |
|-------------------------------|-----------------------------------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                                            |
| <b>INSTALLATION</b>           | Ceiling Recessed                                                                  |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - Ø KIT                                                                     |
| <b>RECESSED DEPTH (MM)</b>    | 75                                                                                |
| <b>INGRESS PROTECTION</b>     | IP20                                                                              |
| <b>WEIGHT (KG)</b>            | 0.2                                                                               |
| <b>ADJUSTABILITY</b>          | 0° to 45° swiveling, 355° rotatable                                               |
| <b>INFORMATION</b>            | REFLECTOR FL-30°<br>EXCL.LED POWER SUPPLY 350-1050mA-DC<br>SPY 20 TUBE B included |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | F                         |
| <b>CERTIFICATES</b> | CB, ENEC                  |

### Lightsource info

|                                    |                                                        |
|------------------------------------|--------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                    |
| <b>LIGHTSOURCE</b>                 | LED array 1-3,1W / CRI>90 (R9: 60) / 3000K / 131-334lm |
| <b>TM-30 VALUES</b>                | rf: 92 / Rg: 99                                        |
| <b>SDCM</b>                        | SDCM3                                                  |
| <b>RISKGROUP</b>                   | RG2                                                    |
| <b>LM80</b>                        | L90B10 > 150000                                        |
| <b>BEAMANGLE</b>                   | 30°                                                    |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 334lm // 3,1W // 109lm/W                               |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 252lm // 3,6W // 71lm/W                                |

### Requirements

MOUNTING KIT SPY 20 L TRIMLESS

LED POWER SUPPLY 350 / 500 / 700 / 1050mA-DC DIM (Remote)

For detailed installation instructions, please consult the manual : [27217\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## SPY 20 L TRIMLESS 93030

27217 9320 FG

### CEILING COMPATIBILITY

| Ceiling Type                                                                     | Mounting Kit          |                                                                                                                                                     |
|----------------------------------------------------------------------------------|-----------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|
|  | <b>System ceiling</b> |  15212 2060 - MOUNTING KIT SPY 20 L TRIMLESS <span>Required</span> |
|  | <b>Plasterboard</b>   |  15212 2060 - MOUNTING KIT SPY 20 L TRIMLESS <span>Required</span> |
|  | <b>Stucanet</b>       |  15212 2060 - MOUNTING KIT SPY 20 L TRIMLESS <span>Required</span> |

### FINISH YOUR SPECIFICATION






#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the 'I' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current

|                                                                                    |                                                                                                                                                        |                            |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------|
|  | <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1<br><b>Dimtype: 1-10V</b><br><b>Cutout dimension (mm): 30</b>                  | 3->14 <input type="text"/> |
|  | <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 45</b>                   | 3->14 <input type="text"/> |
|  | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL<br><b>Dimtype: non-dimmable</b><br><b>Cutout dimension (mm): 30</b>            | 3->14 <input type="text"/> |
|  | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br><b>Dimtype: WDL = wireless dimmable</b><br><b>Cutout dimension (mm): 45</b> | 3->14 <input type="text"/> |
|  | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1<br><b>Dimtype: 1-10V</b><br><b>Cutout dimension (mm): 30</b>                  | 3->14 <input type="text"/> |

SPY 20 L TRIMLESS 93030

27217 9320 FG

|                                                                                    |                                                                          |                                   |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|-----------------------------------|--------------------------|
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 3->14                             | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                                   |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                   |                          |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 3->14                             | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                                   |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                                   |                          |
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 3->14                             | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                                   |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                   |                          |
|    | <b>300 48 700 ED1</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM1 | 3->14                             | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V                                                           |                                   |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                                   |                          |
|  | <b>300 48 700 ED5</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5 | 3->14                             | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                                   |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                   |                          |
|  | <b>300 48 700 MDL</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W MDL  | 3->14                             | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                                   |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                                   |                          |
|  | <b>300 48 700 WDL</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W WDL  | 3->14                             | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                                   |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                   |                          |
|  | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 16   16   16                      | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |                                   |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |                                   |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 26(25)   25(25)   24(19)   19(12) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                                   |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |                                   |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 4->18(15)   17(10)   16(7)        | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                                   |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                                   |                          |

SPY 20 L TRIMLESS 93030







27217 9320 FG

|                                                                                    |                                                                                                                                 |                                      |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------|--------------------------------------|--------------------------|
|    | <b>300 90 67</b><br>LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9<br>Dimtype: 1-10V or DALI or push button               | 3->15   3->15   3->15                | <input type="checkbox"/> |
|    | <b>300 90 68</b><br>LED POWER SUPPLY MULTI-POWER DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 72                             | 2->17(15)   2->17(10)   2->15(7)   - | <input type="checkbox"/> |
|    | <b>300 90 69</b><br>LED POWER SUPPLY MULTI-POWER HV DIM9<br>Dimtype: 1-10V or DALI or push button<br>Cutout dimension (mm): 84  | 8->40(39)   40(28)   29(19)   -      | <input type="checkbox"/> |
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br>Dimtype: 1-10V or push button<br>Cutout dimension (mm): 55            | 6->17(15)   2->14(10)   2->10(7)   - | <input type="checkbox"/> |
|  | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 55                       | 4->17(15)   2->14(10)   2->9(7)   -  | <input type="checkbox"/> |
|  | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 90                      | 17->29   12->29   10->30   10->23    | <input type="checkbox"/> |
|  | <b>300 90 136</b><br>LED POWER SUPPLY MULTI-POWER HC DIM9<br>Dimtype: 1-10V or DALI or push button<br>Cutout dimension (mm): 90 | 15(12)                               | <input type="checkbox"/> |
|  | <b>300 90 148</b><br>LED POWER SUPPLY 1050mA-DC / 22W<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 48                     | 7(3)                                 | <input type="checkbox"/> |
|  | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 50                         | 6->15   4->15   4->15   4->13        | <input type="checkbox"/> |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 54                           | 4->19   4->19   4->17   4->12        | <input type="checkbox"/> |

# DELTALIGHT

## SPY 20 L TRIMLESS 93030







27217 9320 FG

|                                                                                    |                                                                                                                                             |                                   |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------|--------------------------|
|    | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 54                                | 4->19   4->19   4->18   4->12     | <input type="checkbox"/> |
|    | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 84              | 25(25)   25(25)   25(20)   20(13) | <input type="checkbox"/> |
|    | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 54      | 4->19   4->19   4->17   4->12     | <input type="checkbox"/> |
|    | <b>21012 0258</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 50 | 7->10                             | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 50 | 10->15   -   -   -                | <input type="checkbox"/> |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 55 | 6->10   6->9   -                  | <input type="checkbox"/> |
|  | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 55 | 12->18   12->17   -               | <input type="checkbox"/> |
|  | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 48 | 3->15   3->14   3->9   -          | <input type="checkbox"/> |
|  | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 40             | 5->7                              | <input type="checkbox"/> |
|  | <b>21012 0318</b><br>LED POWER SUPPLY 500mA / 10W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 40               | 5->7                              | <input type="checkbox"/> |


# DELTALIGHT

## SPY 20 L TRIMLESS 93030

27217 9320 FG

|                                                                                    |                                                                      |           |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|-----------|--------------------------|
|    | <b>21012 0328</b> LED POWER SUPPLY 700mA / 15W DIM8                  | 5->7      | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |           |                          |
| Cutout dimension (mm): 40                                                          |                                                                      |           |                          |
|   | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 2->17(15) | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |           |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |           |                          |
|   | <b>21012 0490</b> LED POWER SUPPLY 700mA-DC / 30W IP68               | 2->14(7)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |           |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |           |                          |
|   | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 2->17(10) | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |           |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |           |                          |
|  | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 3->15     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |           |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |           |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 3->15     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |           |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |           |                          |
|  | <b>21032 0315</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5 | 3->14     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |           |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |           |                          |

### Mounting kits

|                                                                                    |                                                  |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------|--------------------------|
|  | <b>15212 2060</b> MOUNTING KIT SPY 20 L TRIMLESS | <input type="checkbox"/> |
| Cutout dimension (mm): 50                                                          |                                                  |                          |

Notes:

# DELTALIGHT

## **SPY 20 L TRIMLESS 93030**

27217 9320 FG