



## SPM20 - SPY 392 AIR 93040

29813 9330 B

AVAILABLE IN  
**BLACK** 29813 9330 B  
**FLEMISH BRONZE** 29813 9330 FBR  
**FLEMISH GOLD** 29813 9330 FG  
**GOLD COLOURED** 29813 9330 GC  
**WHITE** 29813 9330 W



 [View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	rectangle - KIT
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.5
<b>ADJUSTABILITY</b>	0° to 85° swiveling, 355° rotatable
<b>INFORMATION</b>	REFLECTOR WFL-40° EXCL.LED POWER SUPPLY 350-500mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	E

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	2 x (LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm)
<b>TM-30 VALUES</b>	rf: 90 / Rg: 99
<b>SDCM</b>	SDCM1
<b>RISKGROUPE</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>BEAMANGLE</b>	40°
<b>LED TECHNICS (LIGHT SOURCE)</b>	2178lm // 17,2W // 127lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	1766lm // 19,8W // 89lm/W

### Requirements

SPM20 - AIR KIT 1  
 SPY 39 TUBE or VISOR 39  
 LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : [29813\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## SPM20 - SPY 392 AIR 93040

29813 9330 B

### CEILING COMPATIBILITY

Ceiling Type

Mounting Kit



Ventilation in plasterboard




29810 1010 - SPM20 - AIR KIT 1

Required

### FINISH YOUR SPECIFICATION

#### AIR kit for M20



**29810 1010** SPM20 - AIR KIT 1



Cutout dimension (mm): 50 x 310


#### LED power supplies

# of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

Dimtype: DALI

Cutout dimension (mm): 45




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1

Dimtype: non-dimmable

Cutout dimension (mm): 30




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1

Dimtype: 1-10V

Cutout dimension (mm): 30

# DELTALIGHT

## SPM20 - SPY 392 AIR 93040

29813 9330 B



**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1



Dimtype: DALI

Cutout dimension (mm): 45



**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1



Dimtype: non-dimmable

Cutout dimension (mm): 30




**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1



Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6

1 | 1



Dimtype: mains (phase cut-off) or push button

Cutout dimension (mm): 56




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

2(2) | 2(2)



Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 82




**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7

1(1) | 1(1/2)



Dimtype: 1-10V or push button

Cutout dimension (mm): 72




**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

1 | -



Dimtype: 1-10V or DALI or push button




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

1(1) | 1(1/2)



Dimtype: DALI

Cutout dimension (mm): 72




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9

3(3) | 3(2)



Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 84



**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7

1(1) | 1(1/2)



Dimtype: 1-10V or push button

Cutout dimension (mm): 55

# DELTALIGHT

## SPM20 - SPY 392 AIR 93040

29813 9330 B




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

1(1) | 1(1/2)

Dimtype: DALI

Cutout dimension (mm): 55



**300 90 135** LED POWER SUPPLY MULTI-POWER HV

2 | 2

Dimtype: non-dimmable

Cutout dimension (mm): 90




**21012 0010** LED POWER SUPPLY MULTI POWER

1 | 1

Dimtype: non-dimmable

Cutout dimension (mm): 50




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1

1 | 1

Dimtype: 1-10V

Cutout dimension (mm): 54




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5

1 | 1

Dimtype: DALI

Cutout dimension (mm): 54




**21012 004W** LED POWER SUPPLY MULTI-POWER WDL

2(2) | 1(1)

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 84




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

1 | 1

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 54




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

1 | -

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 50




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1/2

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 55



**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

1


Dimtype: mains (phase cut-off)

Cutout dimension (mm): 55

# DELTALIGHT

## SPM20 - SPY 392 AIR 93040

29813 9330 B




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1|1

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 48**




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8

1/2

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8

1/2

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

1(1)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68

1(1/2)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

**Dimtype: DALI**

**Cutout dimension (mm): 30**




**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1

**Dimtype: DALI**

**Cutout dimension (mm): 30**

### Light altering devices



**24144 0030 B** VISOR 39 B


# DELTALIGHT

## SPM20 - SPY 392 AIR 93040

29813 9330 B

### Finish your product

---



**24144 0010 B** SPY 39 TUBE B

---

**24144 0010 FBR** SPY 39 TUBE FBR

---

**24144 0010 FG** SPY 39 TUBE FG

---

**24144 0010 GC** SPY 39 TUBE GC

---

**24144 0010 W** SPY 39 TUBE W



**24144 0070** SPY 39 TUBE SBL

Notes: