





## SPY 39 CLIP WALLWASH 930

24152 9300 B-B

AVAILABLE IN

- BLACK-BLACK** 24152 9300 B-B
- BRUSHED ALU-BLACK** 24152 9300 BRA-B
- BRUSHED ANTHRACITE-BLACK** 24152 9300 BRAT-B
- BRUSHED COPPER-BLACK** 24152 9300 BRCU-B
- BRUSHED GOLD-BLACK** 24152 9300 BRG-B
- BRUSHED OLD BRONZE-BLACK** 24152 9300 BROB-B
- FLEMISH BRONZE-BLACK** 24152 9300 FBR-B
- FLEMISH GOLD-BLACK** 24152 9300 FG-B
- FULL WHITE** 24152 9300 FW
- GOLD COLORED-BLACK** 24152 9300 GC-B
- WHITE-WHITE** 24152 9300 W-W



 [View on website](#)



General info	
<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Semi-recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	round - 43
<b>RECESSED DEPTH (MM)</b>	40
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3
<b>ADJUSTABILITY</b>	0° to 85° swiveling, 355° rotatable
<b>INFORMATION</b>	WALLWASH LENS EXCL.LED POWER SUPPLY 350mA-DC

Electrical info	
<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	E
<b>CERTIFICATES</b>	LCA

Lightsource info	
<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8W / CRI>90 (R9: 52) / 3000K / 787lm
<b>TM-30 VALUES</b>	rf: 90 / Rg: 99
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	787lm // 5,8W // 135lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	431lm // 6,7W // 65lm/W

Requirements	
LED POWER SUPPLY 350mA-DC DIM	







For detailed installation instructions, please consult the manual : [24152\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## SPY 39 CLIP WALLWASH 930

24152 9300 B-B

### CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Wood	-
 Concrete	-
 Hollow-core slab	-
 Stretched ceiling	-

### FINISH YOUR SPECIFICATION


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30



**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45

# DELTALIGHT

## SPY 39 CLIP WALLWASH 930

24152 9300 B-B



**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30



**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45



**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30



**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6

2 | 2

Dimtype: mains (phase cut-off) or push button

Cutout dimension (mm): 56



**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

4(4)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 82



**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7

2(2) | 2(1)

Dimtype: 1-10V or push button

Cutout dimension (mm): 72



**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

2 | -

Dimtype: 1-10V or DALI or push button



**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

2(2)

Dimtype: DALI

Cutout dimension (mm): 72



**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 84

# DELTALIGHT

## SPY 39 CLIP WALLWASH 930

24152 9300 B-B




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7

3(2)

**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 55**



**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

2(2)

**Dimtype: DALI**

**Cutout dimension (mm): 55**




**300 90 135** LED POWER SUPPLY MULTI-POWER HV

3->4 | 2->4

**Dimtype: non-dimmable**

**Cutout dimension (mm): 90**




**21012 0010** LED POWER SUPPLY MULTI POWER

2 | 2

**Dimtype: non-dimmable**

**Cutout dimension (mm): 50**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1

3 | 3

**Dimtype: 1-10V**

**Cutout dimension (mm): 54**



**21012 0035** LED POWER SUPPLY MULTI POWER DIM5

3

**Dimtype: DALI**

**Cutout dimension (mm): 54**



**21012 004W** LED POWER SUPPLY MULTI-POWER WDL

4(4) | 3(3)

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 84**



**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

3 | 3

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 54**



**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

2->2

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 50**



**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**

# DELTALIGHT

## SPY 39 CLIP WALLWASH 930

24152 9300 B-B




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

2->2



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 48**




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8

1



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8

1



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

2(2)



**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2



**Dimtype: DALI**

**Cutout dimension (mm): 30**



**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2



**Dimtype: DALI**

**Cutout dimension (mm): 30**

Notes: