



## GYN W M 927

100054 9200



 [View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Wall Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	rectangle - 225 x 305
<b>RECESSED DEPTH (MM)</b>	65
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	min.9 - max.15
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	2.8
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	EXCL.LED POWER SUPPLY 350mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	F

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED cluster 8,7W / CRI>90 / 2700K / 938lm
<b>LED TECHNICS (LIGHT SOURCE)</b>	938lm // 8,7W // 108lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	361lm // 10W // 36lm/W

### Requirements

LED POWER SUPPLY 350mA-DC DIM

For detailed installation instructions, please consult the manual : [100054\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## GYN W M 927

100054 9200

### FINISH YOUR SPECIFICATION


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 90 91** LED POWER SUPPLY 350mA-DC / 15W

1(1)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 40**



**300 90 110** LED POWER SUPPLY 350mA-DC / 10W DIM8

1

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 42**

Notes: