





## GYN 1 92733 W

100066 9220 W

AVAILABLE IN  
**WHITE** 100066 9220 W



[View on website](#)

### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	square - 140 x 140
<b>RECESSED DEPTH (MM)</b>	80
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	min.7 - max.18
<b>INGRESS PROTECTION</b>	IP23/20
<b>WEIGHT (KG)</b>	1
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 350-500mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	E

### Lightsource info




<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
<b>TM-30 VALUES</b>	Rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	1041lm // 8,6W // 121lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	844lm // 10W // 85lm/W

### Requirements










LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual: [100066\\_XXX0\\_HAND.pdf](#)

CEILING COMPATIBILITY


Ceiling Type	Mounting Kit
 <b>System ceiling</b>	-
 <b>Plasterboard</b>	-
 <b>Stucanet</b>	-

FINISH YOUR SPECIFICATION

LED power supplies			#
	<b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9	1->4(4) / 1->4(4)	<input type="checkbox"/>
	<b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5	1->2(1) / 1->2(1)	<input type="checkbox"/>
	<b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9	2->5(5) / 1->5(3)	<input type="checkbox"/>
	<b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1(1)	<input type="checkbox"/>
	<b>300 90 125</b> LED POWER SUPPLY MULTI-POWER MINI DIM5	1->2(1) / 1(1)	<input type="checkbox"/>
	<b>21012 005W</b> LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->2 / 1->2	<input type="checkbox"/>
	<b>21012 0258</b> LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	1	<input type="checkbox"/>
	<b>21012 0278</b> LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1	<input type="checkbox"/>
	<b>21012 0288</b> LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2	<input type="checkbox"/>


GYN 1 92733 W

100066 9220 W




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2 / 1 ☐




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

1-2(2) ☐




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68

1-2(1) ☐



**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1 ☐



**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1 ☐

Notes: