



## BOXY 2 L 93033 DIM8 W-W

10727 9328 W-W

AVAILABLE IN



**BLACK-BLACK** 10727 9328 B-B

**BLACK-FLEMISH BRONZE** 10727 9328 B-FBR

**BLACK-FLEMISH GOLD** 10727 9328 B-FG

**BLACK-GOLD MATT** 10727 9328 B-MMAT

**WHITE-WHITE** 10727 9328 W-W



 [View on website](#)

### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Surface mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.8
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	2 x REFLECTOR FL-33° INCL.DIMMABLE POWER SUPPLY 350mA-DC >> B-MMAT only interior use - other colours also exterior use

### Electrical info

<b>ELECTRICAL</b>	220-240V / 50-60Hz
<b>CLASS</b>	II
<b>POWER SUPPLY</b>	YES
<b>DIM TYPE</b>	mains (phase cut-off)
<b>ENERGY CLASS</b>	C
<b>CERTIFICATES</b>	CB, EAC, ENEC, RCM

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	2 x (LED array 5,8W / CRI>90 (R9: 52) / 3000K / 787lm)
<b>TM-30 VALUES</b>	Rf: 90 / Rg: 99
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	1574lm // 11,6W // 135lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	1256lm // 13W // 94lm/W

### Accessories

BOXY HONEYCOMB  
BOXY SOFTENING LENS  
BOXY GLASS SBL

BOXY 2 L 93033 DIM8 W-W

10727 9328 W-W







For detailed installation instructions, please consult the manual: [10727\\_XXXX\\_HAND.pdf](#)

FINISH YOUR SPECIFICATION

Control gear, ballast and transformers

	<b>300 90 004 ED8</b> WIRELESS CONTROL DIM8	<input type="checkbox"/>
--	---	--------------------------

Light altering devices

	<b>251 70 03 01 B</b> BOXY HONEYCOMB B	<input type="checkbox"/>
	<b>251 70 03 01 W</b> BOXY HONEYCOMB W	<input type="checkbox"/>
	<b>251 70 03 04 B</b> BOXY SOFTENING LENS B	<input type="checkbox"/>
	<b>251 70 03 04 W</b> BOXY SOFTENING LENS W	<input type="checkbox"/>
	<b>251 70 03 05 B</b> BOXY GLASS SBL B	<input type="checkbox"/>
	<b>251 70 03 05 W</b> BOXY GLASS SBL W	<input type="checkbox"/>



## **BOXY 2 L 93033 DIM8 W-W**

10727 9328 W-W

Notes: