





REO 93033 S2 W  
202 262 811 932 W

AVAILABLE IN  
**BLACK** 202 262 811 932 B  
**WHITE** 202 262 811 932 W



 [View on website](#)

General info

|                        |  |
|------------------------|--|
| LOCATION               | indoor   |
| INSTALLATION           | Ceiling Recessed                                       |
| CUTOUT SHAPE/SIZE (MM) | round - 76   |
| RECESSED DEPTH (MM)    | 55   |
| INGRESS PROTECTION     | IP20   |
| WEIGHT (KG)            | 0.2  |
| ADJUSTABILITY          | non adjustable   |
| INFORMATION            | REFLECTOR FL-33°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

Electrical info

|              |                           |
|--------------|---------------------------|
| CLASS        | III                       |
| DIM TYPE     | depending on power supply |
| ENERGY CLASS | D                         |
| CERTIFICATES | CB, EAC, ENEC             |

Lightsource info











|                             |   |
|-----------------------------|---|
| LIGHTSOURCE NAME            | LED   |
| LIGHTSOURCE                 | LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm |
| TM-30 VALUES                | rf: 90 / Rg: 99   |
| SDCM                        | SDCM1   |
| RISKGROUP                   | RG1   |
| LM80                        | L90B10 > 50000  |
| LED TECHNICS (LIGHT SOURCE) | 1089lm // 8,6W // 127lm/W                                 |
| LED TECHNICS (LUMINAIRE)    | 887lm // 10W // 90lm/W                                    |

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM


For detailed installation instructions, please consult the manual: [202\\_262\\_811\\_XXX\\_HAND.pdf](#)

CEILING COMPATIBILITY

| Ceiling Type   | Mounting Kit |
|--|--------------|
|  <b>System ceiling</b>               | -            |
|  <b>Plasterboard</b>                 | -            |
|  <b>Stucanet</b>                     | -            |
|  <b>Wood</b>                         | -            |
|  <b>Concrete</b>                     | -            |
|  <b>Concrete + plaster</b>          | -            |
|  <b>Lintel + plaster</b>           | -            |
|  <b>Hollow-core slab</b>           | -            |
|  <b>Hollow-core slab + plaster</b> | -            |
|  <b>Stretched ceiling</b>          | -            |

FINISH YOUR SPECIFICATION

Emergency units












**21032 0270 B** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B

☐

**21032 0270 W** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W


☐

REO 93033 S2 W  
202 262 811 932 W

| LED power supplies   |                   |  | #  |
|--|-------------------|--|--|
|    | <b>300 90 63</b>  | LED POWER SUPPLY MULTI-POWER DIM9        | 1->4(4) / 1->4(4) <input type="checkbox"/> |
|    | <b>300 90 68</b>  | LED POWER SUPPLY MULTI-POWER DIM5        | 1->2(1) / 1->2(1) <input type="checkbox"/> |
|    | <b>300 90 69</b>  | LED POWER SUPPLY MULTI-POWER HV DIM9     | 2->6(6) / 1->6(4) <input type="checkbox"/> |
|   | <b>300 90 91</b>  | LED POWER SUPPLY 350mA-DC / 15W          | 1 <input type="checkbox"/>                 |
|  | <b>300 90 110</b> | LED POWER SUPPLY 350mA-DC / 10W DIM8     | 1 <input type="checkbox"/>                 |
|  | <b>300 90 116</b> | LED POWER SUPPLY 350mA-DC / 18W DIM8     | 2->2 <input type="checkbox"/>              |
|  | <b>300 90 124</b> | LED POWER SUPPLY MULTI-POWER DIM7        | 1->2(1) / 1(1) <input type="checkbox"/>    |
|  | <b>300 90 125</b> | LED POWER SUPPLY MULTI-POWER MINI DIM5   | 1->2(1) / 1(1) <input type="checkbox"/>    |
|  | <b>21012 005W</b> | LED POWER SUPPLY MULTI-POWER COMPACT WDL | 1->2 / 1->2 <input type="checkbox"/>       |


REO 93033 S2 W

202 262 811 932 W




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

1 ☐




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1 ☐




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

2->2 ☐




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2/1 ☐




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

1-2(2) ☐




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68

1-2(1) ☐




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1 ☐



**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1 ☐



**21032 0375** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W PRO DIM5

1 ☐



**REO 93033 S2 W**

202 262 811 932 W

Notes: