



## DEEP RINGO LED 92733 BROB

202 272 811 922 BROB

AVAILABLE IN

**BLACK** 202 272 811 922 B

**BRUSHED ALU** 202 272 811 922 BRA

**BRUSHED ANTHRACITE** 202 272 811 922 BRAT

**BRUSHED COPPER** 202 272 811 922 BRCU

**BRUSHED GOLD** 202 272 811 922 BRG

**BRUSHED OLD BRONZE** 202 272 811 922 BROB



**FLEMISH BRONZE** 202 272 811 922 FBR

**FLEMISH GOLD** 202 272 811 922 FG

**GOLD COLOURED** 202 272 811 922 GC

**PIANO BLACK** 202 272 811 922 PB

**WHITE** 202 272 811 922 W



[View on website](#)

### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	round - 76
<b>RECESSED DEPTH (MM)</b>	90
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	min.5
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.2
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	REFLECTOR FL-33° EXCLLED POWER SUPPLY 350-500mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	E
<b>CERTIFICATES</b>	CB, EAC, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
<b>TM-30 VALUES</b>	rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	1041lm // 8,6W // 121lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	768lm // 10W // 78lm/W

### Requirements











LED POWER SUPPLY 350 / 500mA-DC DIM

**DEEP RINGO LED 92733 BROB**

202 272 811 922 BROB

For detailed installation instructions, please consult the manual: [202\\_272\\_811\\_XXX\\_HAND.pdf](#)

**CEILING COMPATIBILITY**

Ceiling Type	Mounting Kit
 <b>System ceiling</b>	-
 <b>Plasterboard</b>	-
 <b>Stucanet</b>	-
 <b>Wood</b>	-
 <b>Concrete</b>	-
 <b>Concrete + plaster</b>	-
 <b>Lintel + plaster</b>	-
 <b>Hollow-core slab</b>	-
 <b>Hollow-core slab + plaster</b>	-
 <b>Stretched ceiling</b>	-


## DEEP RINGO LED 92733 BROB

202 272 811 922 BROB

### FINISH YOUR SPECIFICATION

#### Emergency units

---



**21032 0270 B** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B










☐

---






**21032 0270 W** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W

☐

**DEEP RINGO LED 92733 BROB**  
 202 272 811 922 BROB

LED power supplies			#
	<b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9	1->4(4) / 1->4(4)	<input type="checkbox"/>
	<b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5	1->2(1) / 1->2(1)	<input type="checkbox"/>
	<b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9	2->6(6) / 1->6(4)	<input type="checkbox"/>
	<b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7	1->2(1) / 1(1)	<input type="checkbox"/>
	<b>300 90 125</b> LED POWER SUPPLY MULTI-POWER MINI DIM5	1->2(1) / 1(1)	<input type="checkbox"/>
	<b>21012 005W</b> LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->2 / 1->2	<input type="checkbox"/>
	<b>21012 0258</b> LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	1	<input type="checkbox"/>
	<b>21012 0278</b> LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1	<input type="checkbox"/>
	<b>21012 0288</b> LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2	<input type="checkbox"/>

**DEEP RINGO LED 92733 BROB**  
 202 272 811 922 BROB

	<b>21012 0298</b> LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	2 / 1 <input type="checkbox"/>
	<b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68	1-2(2) <input type="checkbox"/>
	<b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68	1-2(1) <input type="checkbox"/>
	<b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1 <input type="checkbox"/>
	<b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1 <input type="checkbox"/>

Notes: