





## M26L - SPY 391 92740 MDL B

### 23258 9230 B

AVAILABLE IN

**BLACK** 23258 9230 B  
**BRUSHED ALU** 23258 9230 BRA  
**BRUSHED ANTHRACITE** 23258 9230 BRAT  
**BRUSHED COPPER** 23258 9230 BRCU  
**BRUSHED GOLD** 23258 9230 BRG  
**BRUSHED OLD BRONZE** 23258 9230 BROB  
**FLEMISH BRONZE** 23258 9230 FBR  
**FLEMISH GOLD** 23258 9230 FG  
**GOLD COLOURED** 23258 9230 GC  
**PIANO BLACK** 23258 9230 PB  
**WHITE** 23258 9230 W



[View on website](#)

#### General info

|                           |   |
|---------------------------|---|
| <b>LOCATION</b>           | indoor  |
| <b>INSTALLATION</b>       | Low voltage systems Low voltage system mounted    |
| <b>INGRESS PROTECTION</b> | IP20  |
| <b>WEIGHT (KG)</b>        | 0.3   |
| <b>ADJUSTABILITY</b>      | 0° to 85° swiveling, 360° rotatable               |
| <b>INFORMATION</b>        | REFLECTOR WFL-40°<br>EXCL.LED POWER SUPPLY 48V-DC |

#### Electrical info

|                     |                                    |
|---------------------|------------------------------------|
| <b>ELECTRICAL</b>   | 48V-DC                             |
| <b>CLASS</b>        | III                                |
| <b>DIM TYPE</b>     | MDL = 1-10V or DALI or push button |
| <b>ENERGY CLASS</b> | E                                  |
| <b>CERTIFICATES</b> | ENEC, LCA                          |

#### Lightsource info

|                                    |   |
|------------------------------------|---|
| <b>LIGHTSOURCE NAME</b>            | LED   |
| <b>LIGHTSOURCE</b>                 | LED array 8,6W / CRI>90 (R9: 60) / 2700K / 1041lm |
| <b>TM-30 VALUES</b>                | Rf: 89 / Rg: 100                                  |
| <b>SDCM</b>                        | SDCM1   |
| <b>RISKGROUP</b>                   | RG1   |
| <b>LM80</b>                        | L90B10 > 50000                                    |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1041lm // 8,6W // 121lm/W                         |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 844lm // 10W // 85lm/W                            |

#### Remarks

[Take a look at our MAGNETIC PROFILES movie](#)



## M26L - SPY 391 92740 MDL B

23258 9230 B

### Requirements

---

SPY 39 TUBE or VISOR 39  
LED POWER SUPPLY 48V-DC

### Options

---

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual: [23258\\_XXX0\\_HAND.pdf](#)

**M26L - SPY 391 92740 MDL B**  
 23258 9230 B

FINISH YOUR SPECIFICATION

Current supply
 #



**21032 0030** SMART 48 MODULATOR PLUG-IN WD


19
 ☐

SMART 48
 #



**300 90 011** SMART 48 MODULATOR DIM9


19
 ☐



**300 90 012** SMART 48 MODULATOR WD


19
 ☐

LED power supplies
 #



**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN

10
 ☐



**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN

24
 ☐



**21012 0230** LED POWER SUPPLY 48V-DC / 100W

10
 ☐



**21012 0240** LED POWER SUPPLY 48V-DC / 200W

20
 ☐

Light altering devices



24144 0030 B VISOR 39 B

☐

Finish your product



24144 0010 B SPY 39 TUBE B

☐

24144 0010 FBR SPY 39 TUBE FBR

☐

24144 0010 FG SPY 39 TUBE FG

☐

24144 0010 GC SPY 39 TUBE GC

☐

24144 0010 W SPY 39 TUBE W

☐







24144 0070 SPY 39 TUBE SBL

☐

















M26L - SPY 391 92740 MDL B  
23258 9230 B

COMPATIBLE COMPOSABLES

SHIFTLINE M26L FLOOR Available Colours

|   |                                   |   |
|---|-----------------------------------|---|
|  | <b>29321 0010</b> SLM26L F MDL    |  |
|  | <b>29322 002W</b> SLM26L F MDL WD |  |

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX) Available Colours

|   |                                       |   |
|---|---------------------------------------|---|
|    | <b>23358 0000</b> SLM26L - PROFILE    |     |
|  | <b>23358 0010</b> SLM26L - PROFILE 1m |     |
|  | <b>23358 0020</b> SLM26L - PROFILE 2m |     |
|  | <b>23358 0030</b> SLM26L - PROFILE 3m |     |

Notes: