



## MICROGRID IN 1 92730 W-B

100055 9220 W-B



AVAILABLE IN

**BLACK-BLACK** 100055 9220 B-B

**BLACK-WHITE** 100055 9220 B-W

**WHITE-BLACK** 100055 9220 W-B

**WHITE-WHITE** 100055 9220 W-W



[View on website](#)

### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	rectangle - 62 x 59
<b>RECESSED DEPTH (MM)</b>	75
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	min.12 - max.25
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.2
<b>ADJUSTABILITY</b>	0° to 20° swiveling, 350° rotatable
<b>INFORMATION</b>	LENS FL-30° EXCL.LED POWER SUPPLY 350mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	F
<b>CERTIFICATES</b>	CB, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 3,9W / CRI>90 (R9: 56) / 2700K / 385lm
<b>TM-30 VALUES</b>	rf: 91 / Rg: 99
<b>SDCM</b>	SDCM2
<b>RISKGROUPE</b>	RG2 (threshold 0,6m)
<b>LM80</b>	L90B10 > 41000
<b>LED TECHNICS (LIGHT SOURCE)</b>	385lm // 3,9W // 98lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	292lm // 4W // 65lm/W

### Requirements

LED POWER SUPPLY 350mA-DC DIM

### Accessories

MICRO VISOR

**MICROGRID IN 1 92730 W-B**

100055 9220 W-B

For detailed installation instructions, please consult the manual: [100055\\_XXX0\\_HAND.pdf](#)

**CEILING COMPATIBILITY**

Ceiling Type	Mounting Kit
 <b>System ceiling</b>	-
 <b>Plasterboard</b>	-
 <b>Stucanet</b>	-
 <b>Wood</b>	-
 <b>Stretched ceiling</b>	-


## MICROGRID IN 1 92730 W-B

100055 9220 W-B

### FINISH YOUR SPECIFICATION

#### Emergency units

---



**21032 0270 B** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B

☐










---

**21032 0270 W** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W

☐


MICROGRID IN 1 92730 W-B

100055 9220 W-B

LED power supplies			#
	<b>300 90 63</b>	LED POWER SUPPLY MULTI-POWER DIM9	1->6(6) <input type="checkbox"/>
	<b>300 90 68</b>	LED POWER SUPPLY MULTI-POWER DIM5	1->4(3) <input type="checkbox"/>
	<b>300 90 69</b>	LED POWER SUPPLY MULTI-POWER HV DIM9	3->9(9) <input type="checkbox"/>
	<b>300 90 124</b>	LED POWER SUPPLY MULTI-POWER DIM7	2->4(3) <input type="checkbox"/>
	<b>300 90 125</b>	LED POWER SUPPLY MULTI-POWER MINI DIM5	2->4(3) <input type="checkbox"/>
	<b>21012 0010</b>	LED POWER SUPPLY MULTI POWER	2->3 <input type="checkbox"/>
	<b>21012 0021</b>	LED POWER SUPPLY MULTI POWER DIM1	2->4 <input type="checkbox"/>
	<b>21012 0035</b>	LED POWER SUPPLY MULTI POWER DIM5	2->4 <input type="checkbox"/>
	<b>21012 005W</b>	LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->4 <input type="checkbox"/>


MICROGRID IN 1 92730 W-B

100055 9220 W-B




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2 ☐




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

3->3 ☐




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3 ☐



**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68


1->4(3) ☐



**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3 ☐

Light altering devices



**10034 0010 B** MICRO VISOR B

☐

Notes: