



## NIME II WALLWASH 927

26416 9200 B

AVAILABLE IN  
**BLACK** 26416 9200 B  
**WHITE** 26416 9200 W



 [View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	round - 67
<b>RECESSED DEPTH (MM)</b>	90
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	9,5-12,5
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	EXCL.LED POWER SUPPLY 350-700mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	G

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED cluster 2-4,3W / CRI>90 (R9: 50) / 2700K / 222-392lm
<b>TM-30 VALUES</b>	Rf: 92 / Rg: 100
<b>SDCM</b>	SDCM3
<b>LM80</b>	L80 > 60000
<b>LED TECHNICS (LIGHT SOURCE)</b>	392lm // 4,3W // 91lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	343lm // 4,9W // 69lm/W

### Requirements

LED POWER SUPPLY 350 / 500 / 700mA-DC DIM

For detailed installation instructions, please consult the manual : [26416\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT







## NIME II WALLWASH 927

26416 9200 B

### CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-


### FINISH YOUR SPECIFICATION

LED power supplies	# of Fixtures
	Min current   Max current
<p> # of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</p>	
 <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9 Dimtype: 1-10V or DALI or push button Cutout dimension (mm): 82	12(12)   12(11)   11(9) <input type="checkbox"/>
 <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5 Dimtype: DALI Cutout dimension (mm): 72	8(7)   8(5)   7(3) <input type="checkbox"/>
 <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9 Dimtype: 1-10V or DALI or push button Cutout dimension (mm): 84	4->19(19)   18(13)   13(9) <input type="checkbox"/>
 <b>300 90 91</b> LED POWER SUPPLY 350mA-DC / 15W Dimtype: non-dimmable Cutout dimension (mm): 40	7(4) <input type="checkbox"/>
 <b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7 Dimtype: 1-10V or push button Cutout dimension (mm): 55	3->8(7)   6(5)   4(3) <input type="checkbox"/>

# DELTALIGHT

## NIME II WALLWASH 927

26416 9200 B




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

2->8(7) | 6(5) | 4(3)



**Dimtype: DALI**

**Cutout dimension (mm): 55**




**21012 0010** LED POWER SUPPLY MULTI POWER

3->7 | 2->7 | 2->7



**Dimtype: non-dimmable**

**Cutout dimension (mm): 50**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1

2->9 | 2->9 | 2->8



**Dimtype: 1-10V**

**Cutout dimension (mm): 54**




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5

2->9 | 2->9 | 2->8



**Dimtype: DALI**

**Cutout dimension (mm): 54**




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

2->9 | 2->9 | 2->8



**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 54**




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

3->4



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 50**




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

5->7



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 50**




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

3->4 | 3->4



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

6->8 | 6->8



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**



**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2->7 | 2->6 | 2->4




**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 48**

# DELTALIGHT

## NIME II WALLWASH 927

26416 9200 B




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8

3->3

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8

3->3

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0328** LED POWER SUPPLY 700mA / 15W DIM8

3->3

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

8(7)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21012 0490** LED POWER SUPPLY 700mA-DC / 30W IP68

6(3)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68

8(5)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

7

**Dimtype: DALI**

**Cutout dimension (mm): 30**




**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

7

**Dimtype: DALI**

**Cutout dimension (mm): 30**



**21032 0315** LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

6

**Dimtype: DALI**

**Cutout dimension (mm): 30**

# DELTALIGHT

## **NIME II WALLWASH 927**

26416 9200 B

Notes: