



## ARTUUR R 92760 W



27711 9220 W

AVAILABLE IN

**BLACK** 27711 9220 B

**GOLD COLOURED** 27711 9220 GC

**WHITE** 27711 9220 W



[View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	round - 72
<b>RECESSED DEPTH (MM)</b>	70
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.4
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	LENS WFL-60° EXCL.LED POWER SUPPLY 350-500mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on type of external power supply
<b>ENERGY CLASS</b>	E
<b>CERTIFICATES</b>	CB, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
<b>TM-30 VALUES</b>	Rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	1041lm // 8,6W // 121lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	592lm // 10W // 60lm/W

### Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

### Options

















MOUNTING KIT TRIMLESS O.F.A. ARTUUR R


# ARTUUR R 92760 W

27711 9220 W

For detailed installation instructions, please consult the manual: [27711\\_XXX0\\_HAND.pdf](#)

## CEILING COMPATIBILITY










Ceiling Type	Mounting Kit	
 <b>System ceiling</b>	 MOUNTING KIT TRIMLESS O.F.A. ARTUUR R	Optional
 <b>Plasterboard</b>	 MOUNTING KIT TRIMLESS O.F.A. ARTUUR R	Optional
 <b>Stucanet</b>	 MOUNTING KIT TRIMLESS O.F.A. ARTUUR R	Optional
 <b>Wood</b>	-	
 <b>Concrete</b>	-	
 <b>Concrete + plaster</b>	 MOUNTING KIT TRIMLESS O.F.A. ARTUUR R	Optional
 <b>Lintel + plaster</b>	 MOUNTING KIT TRIMLESS O.F.A. ARTUUR R	Optional
 <b>Hollow-core slab</b>	-	
 <b>Hollow-core slab + plaster</b>	 MOUNTING KIT TRIMLESS O.F.A. ARTUUR R	Optional
 <b>Stretched ceiling</b>	-	



9


7

ARTUUR R 92760 W  
27711 9220 W

LED power supplies			#
	<b>300 90 63</b>	LED POWER SUPPLY MULTI-POWER DIM9	1->4(4) / 1->3(3) <input type="checkbox"/>
	<b>300 90 68</b>	LED POWER SUPPLY MULTI-POWER DIM5	1->2(2) / 1->2(1) <input type="checkbox"/>
	<b>300 90 69</b>	LED POWER SUPPLY MULTI-POWER HV DIM9	2->6(6) / 1->6(4) <input type="checkbox"/>
	<b>300 90 124</b>	LED POWER SUPPLY MULTI-POWER DIM7	1->2(2) / 1->2(1) <input type="checkbox"/>
	<b>300 90 125</b>	LED POWER SUPPLY MULTI-POWER MINI DIM5	1->2(2) / 1->2(1) <input type="checkbox"/>
	<b>21012 0010</b>	LED POWER SUPPLY MULTI POWER	1->2 / 1->2 <input type="checkbox"/>
	<b>21012 0021</b>	LED POWER SUPPLY MULTI POWER DIM1	1->3 / 1->2 <input type="checkbox"/>
	<b>21012 0035</b>	LED POWER SUPPLY MULTI POWER DIM5	1->3 / 1->2 <input type="checkbox"/>
	<b>21012 005W</b>	LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->3 / 1->2 <input type="checkbox"/>


## ARTUUR R 92760 W

27711 9220 W




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

2->2 / 2->2




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

2->2




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->2 / 1->2 / 1->2




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8

1




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8

1



**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2




**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2



### Mounting kits



**27710 0010** MOUNTING KIT TRIMLESS O.F.A. ARTUUR R





## **ARTUUR R 92760 W**

27711 9220 W

Notes: