



## MICRO REO X 93035 B

302 23 811 932 B



AVAILABLE IN

**BLACK** 302 23 811 932 B

**FLEMISH BRONZE OUTDOOR** 302 23 811 932 FBRX

**ANTHRACITE (DARK GREY)** 302 23 811 932 N

**WHITE** 302 23 811 932 W



[View on website](#)

### General info

<b>LOCATION</b>	indoor-outdoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	round - 46
<b>RECESSED DEPTH (MM)</b>	90
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	min.5
<b>INGRESS PROTECTION</b>	IP43
<b>PROTECTION AGAINST MECHANICAL IMPACT</b>	IK03
<b>WEIGHT (KG)</b>	0.1
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	REFLECTOR FL-35° EXCL.LED POWER SUPPLY 350mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	D
<b>CERTIFICATES</b>	CB, EAC, ENEC

### Lightsources info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8W / CRI>90 (R9: 52) / 3000K / 787lm
<b>TM-30 VALUES</b>	rf: 90 / Rg: 99
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	787lm // 5,8W // 135lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	748lm // 7W // 112lm/W

### Requirements

LED POWER SUPPLY 350mA-DC DIM









**MICRO REO X 93035 B**

302 23 811 932 B

For detailed installation instructions, please consult the manual: [302\\_23\\_811\\_XXX\\_HAND.pdf](#)

**CEILING COMPATIBILITY**










Ceiling Type	Mounting Kit
 <b>Concrete</b>	-
 <b>Concrete + plaster</b>	-
 <b>Lintel + plaster</b>	-
 <b>Hollow-core slab</b>	-
 <b>Hollow-core slab + plaster</b>	-
 <b>Stretched ceiling</b>	-



MICRO REO X 93035 B

302 23 811 932 B


FINISH YOUR SPECIFICATION

LED power supplies			#
	<b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9	1->4(4)	<input type="checkbox"/>
	<b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5	1->2(1)	<input type="checkbox"/>
	<b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9	2->6(6)	<input type="checkbox"/>
	<b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7	2(2)	<input type="checkbox"/>
	<b>300 90 125</b> LED POWER SUPPLY MULTI-POWER MINI DIM5	2(2)	<input type="checkbox"/>
	<b>21012 0010</b> LED POWER SUPPLY MULTI POWER	1->2	<input type="checkbox"/>
	<b>21012 0021</b> LED POWER SUPPLY MULTI POWER DIM1	1->2	<input type="checkbox"/>
	<b>21012 0035</b> LED POWER SUPPLY MULTI POWER DIM5	1->2	<input type="checkbox"/>
	<b>21012 005W</b> LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->2	<input type="checkbox"/>




MICRO REO X 93035 B

302 23 811 932 B




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

1 ☐




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2 ☐



**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

1-2(2) ☐



**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1 ☐

Notes: