





## M - MICROSPY 39 C 92745 MDL B

421 612 811 921 MDL B

AVAILABLE IN

**BLACK** 421 612 811 921 MDL B

**WHITE** 421 612 811 921 MDL W



[View on website](#)

### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Low voltage systems Low voltage system mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.7
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	REFLECTOR WFL-45° EXCL.LED POWER SUPPLY 48V-DC INCL.1 x CABLE 2 x 0.75mm <sup>2</sup>

### Electrical info

<b>ELECTRICAL</b>	48V-DC
<b>CLASS</b>	III
<b>DIM TYPE</b>	MDL = 1-10V or DALI or push button
<b>ENERGY CLASS</b>	D
<b>CERTIFICATES</b>	EAC, ENEC, LCA

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8W / CRI>90 (R9: 60) / 2700K / 753lm
<b>TM-30 VALUES</b>	Rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	753lm // 5,8W // 129lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	507lm // 7W // 76lm/W

### Requirements

LED POWER SUPPLY 48V-DC

### Options

DIMMABLE MODULATOR



## **M - MICROSPY 39 C 92745 MDL B**

421 612 811 921 MDL B

For detailed installation instructions, please consult the manual: [421\\_612\\_811\\_XXX\\_MDL\\_HAND.pdf](#)

M - MICROSPY 39 C 92745 MDL B

421 612 811 921 MDL B

FINISH YOUR SPECIFICATION

Current supply #



**21032 0030** SMART 48 MODULATOR PLUG-IN WD

23 ☐

SMART 48 #



**300 90 011** SMART 48 MODULATOR DIM9


23 ☐



**300 90 012** SMART 48 MODULATOR WD


23 ☐

LED power supplies #



**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN

12 ☐



**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN

29 ☐



**21012 0230** LED POWER SUPPLY 48V-DC / 100W

12 ☐



































**21012 0240** LED POWER SUPPLY 48V-DC / 200W

24 ☐

M - MICROSPY 39 C 92745 MDL B

421 612 811 921 MDL B

COMPATIBLE COMPOSABLES

SHIFTLINE M26H profile		Available Colours
	<b>23359 0000</b> SLM26H - PROFILE	 
	<b>23359 0010</b> SLM26H - PROFILE 1m	 
	<b>23359 0020</b> SLM26H - PROFILE 2m	   
	<b>23359 0030</b> SLM26H - PROFILE 3m	   
SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)		Available Colours
	<b>23358 0000</b> SLM26L - PROFILE	 
	<b>23358 0010</b> SLM26L - PROFILE 1m	 
	<b>23358 0020</b> SLM26L - PROFILE 2m	   
	<b>23358 0030</b> SLM26L - PROFILE 3m	   

M - MICROSPY 39 C 92745 MDL B

421 612 811 921 MDL B

SPLITLINE M20 ST profile

Available Colours



**23397 0000** SPM20 ST - PROFILE



**23397 0020** SPM20 ST - PROFILE 2m




**23397 0030** SPM20 ST - PROFILE 3m




SPLITLINE M20 profile


Available Colours




**420 20 10 00** SPM20 - PROFILE 1m



**420 20 20 00** SPM20 - PROFILE 2m



**420 20 30 00** SPM20 - PROFILE 3m











**23301 0000** SPM20 - PROFILE B



**M - MICROSPY 39 C 92745 MDL B**

421 612 811 921 MDL B

SPLITLINE M52 profile	Available Colours
<div>  </div> <div> <b>420 52 10 00</b> SPM52 - PROFILE 1m </div>	
<div>  </div> <div> <b>420 52 20 00</b> SPM52 - PROFILE 2m </div>	
<div>  </div> <div> <b>420 52 30 00</b> SPM52 - PROFILE 3m </div>	
<div>  </div> <div> <b>24413 0000</b> SPM52 - PROFILE </div>	

Notes: